

RX14T Group

MCK-RX14T User's Manual

Renesas RX Family
RX100 Series

All information contained in these materials, including products and product specifications, represents information on the product at the time of publication and is subject to change by Renesas Electronics Corp. without notice. Please review the latest information published by Renesas Electronics Corp. through various means, including the Renesas Electronics Corp. website (<http://www.renesas.com>).

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.

"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.

"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.

Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.

7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-1 October 2020)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan
www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:
www.renesas.com/contact/.

General Precautions in the Handling of Microprocessing Unit and Microcontroller Unit Products

The following usage notes are applicable to all Microprocessing unit and Microcontroller unit products from Renesas. For detailed usage notes on the products covered by this document, refer to the relevant sections of the document as well as any technical updates that have been issued for the products.

1. Precaution against Electrostatic Discharge (ESD)

A strong electrical field, when exposed to a CMOS device, can cause destruction of the gate oxide and ultimately degrade the device operation. Steps must be taken to stop the generation of static electricity as much as possible, and quickly dissipate it when it occurs. Environmental control must be adequate. When it is dry, a humidifier should be used. This is recommended to avoid using insulators that can easily build up static electricity.

Semiconductor devices must be stored and transported in an anti-static container, static shielding bag or conductive material. All test and measurement tools including work benches and floors must be grounded. The operator must also be grounded using a wrist strap. Semiconductor devices must not be touched with bare hands. Similar precautions must be taken for printed circuit boards with mounted semiconductor devices.

2. Processing at power-on

The state of the product is undefined at the time when power is supplied. The states of internal circuits in the LSI are indeterminate and the states of register settings and pins are undefined at the time when power is supplied. In a finished product where the reset signal is applied to the external reset pin, the states of pins are not guaranteed from the time when power is supplied until the reset process is completed. In a similar way, the states of pins in a product that is reset by an on-chip power-on reset function are not guaranteed from the time when power is supplied until the power reaches the level at which resetting is specified.

3. Input of signal during power-off state

Do not input signals or an I/O pull-up power supply while the device is powered off. The current injection that results from input of such a signal or I/O pull-up power supply may cause malfunction and the abnormal current that passes in the device at this time may cause degradation of internal elements. Follow the guideline for input signal during power-off state as described in your product documentation.

4. Handling of unused pins

Handle unused pins in accordance with the directions given under handling of unused pins in the manual. The input pins of CMOS products are generally in the high-impedance state. In operation with an unused pin in the open-circuit state, extra electromagnetic noise is induced in the vicinity of the LSI, an associated shoot-through current flows internally, and malfunctions occur due to the false recognition of the pin state as an input signal become possible.

5. Clock signals

After applying a reset, only release the reset line after the operating clock signal becomes stable. When switching the clock signal during program execution, wait until the target clock signal is stabilized. When the clock signal is generated with an external resonator or from an external oscillator during a reset, ensure that the reset line is only released after full stabilization of the clock signal. Additionally, when switching to a clock signal produced with an external resonator or by an external oscillator while program execution is in progress, wait until the target clock signal is stable.

6. Voltage application waveform at input pin

Waveform distortion due to input noise or a reflected wave may cause malfunction. If the input of the CMOS device stays in the area between V_{IL} (Max.) and V_{IH} (Min.) due to noise, for example, the device may malfunction. Take care to prevent chattering noise from entering the device when the input level is fixed, and also in the transition period when the input level passes through the area between V_{IL} (Max.) and V_{IH} (Min.).

7. Prohibition of access to reserved addresses

Access to reserved addresses is prohibited. The reserved addresses are provided for possible future expansion of functions. Do not access these addresses as the correct operation of the LSI is not guaranteed.

8. Differences between products

Before changing from one product to another, for example to a product with a different part number, confirm that the change will not lead to problems. The characteristics of a microprocessing unit or microcontroller unit products in the same group but having a different part number might differ in terms of internal memory capacity, layout pattern, and other factors, which can affect the ranges of electrical characteristics, such as characteristic values, operating margins, immunity to noise, and amount of radiated noise. When changing to a product with a different part number, implement a system-evaluation test for the given product.

MCK-RX14T User's Manual

Contents

1. Overview	5
1.1 Presupposition and precautions of this document	5
2. Product Contents	6
3. Product Order Information	6
4. Hardware Configuration and Default Setting	7
4.1 Hardware configuration	7
4.2 Block diagram	11
4.3 Board Layout	12
4.4 Standoffs and Screws	13
4.5 Jumper pin setting	14
4.5.1 Inverter board	14
4.5.2 CPU board	15
4.5.3 Communication board	16
4.6 Hardware Setup	17
4.6.1 Board Connection	17
4.6.2 Power Supply	18
5. Inverter Board Specification	20
5.1 Functions	20
5.1.1 Inverter control circuit block	20
5.1.2 Current detection circuit	21
5.1.3 Overcurrent detection circuit	22
5.1.4 Output voltage detection circuit	23
5.1.5 Voltage generation circuit	23
5.1.6 LED	24
5.1.7 Toggle switch and push switch	24
5.1.8 Variable resistor	24
5.2 Pin assignment	25
5.2.1 CPU board connector	25
5.2.2 Hall sensor signal input	27
5.2.3 Encoder/Inductive position sensor signal input	27
6. CPU Board Specification	28
6.1 Functions	28
6.1.1 Power supply	28
6.1.2 On-board debugger	28

6.1.3	Inverter board connector	29
6.1.4	Serial communication	31
6.1.5	Reset circuit.....	31
6.1.6	LED.....	31
6.1.7	SPI Communication.....	32
6.1.8	Pmod	32
7.	Communication Board Specification	33
7.1	Functions	33
7.1.1	Power supply	33
7.1.2	USB communication.....	33
7.1.3	Serial communication	33
8.	Regulatory information.....	34
8.1	EMC Directive.....	34
8.2	Material Selection, Waste, Recycling and Disposal Standards	34
9.	Design and Manufacture Information	34
10.	Website and Support	34
	Revision History	35

Figure of contents

Figure 2-1 Product contents	6
Figure 4-1 MCK-RX14T block diagram	11
Figure 4-2 Inverter board Layout	12
Figure 4-3 CPU Board Layout	12
Figure 4-4 Communication board Layout	13
Figure 4-5 Standoffs and Screws assembly	13
Figure 4-6 Default jumper pin setting of Inverter board	14
Figure 4-7 Default jumper pin setting of CPU board	15
Figure 4-8 Default jumper pin setting of Communication board	16
Figure 4-9 Board connection	17
Figure 4-10 Power supply from DC jack	18
Figure 4-11 Power supply from terminal block	18
Figure 4-12 Power supply from USB connector	19
Figure 5-1 Illustration of inverter control circuit block	20
Figure 5-2 Current detection circuit	21
Figure 5-3 Overcurrent detection circuit	22
Figure 5-4 Output voltage detection circuit	23
Figure 6-1 JP8 setting	28
Figure 6-2 Board connection of CPU board, INV board and COM board	31

Table of contents

Table 4-1 MCK-RX14T specification (1/4).....	7
Table 4-2 MCK-RX14T specification (2/4).....	8
Table 4-3 MCK-RX14T specification (3/4).....	9
Table 4-4 MCK-RX14T specification (4/4).....	10
Table 4-5 Jumper pin setting of Inverter board	14
Table 4-6 Jumper pin setting of CPU board	15
Table 4-7 Jumper pin setting of Communication board.....	16
Table 4-8 Power supply and driving voltage generation	19
Table 5-1 Voltage generation	23
Table 5-2 LED.....	24
Table 5-3 Toggle switch and push switch.....	24
Table 5-4 Variable resistance specification	24
Table 5-5 CPU board connector (CN3)	25
Table 5-6 CPU board connector (CN4)	26
Table 5-7 Connector for hall sensor signal input (CN6) pin assignment.....	27
Table 5-8 Connector for encoder/inductive position sensor signal input (CN5) pin assignment.....	27
Table 6-1 1st inverter board connector (CN1) pin assignment.....	29
Table 6-2 1st inverter board connector (CN2) pin assignment.....	29
Table 6-3 2nd inverter board connector (CN3) pin assignment	30
Table 6-4 2nd inverter board connector (CN4) pin assignment	30
Table 6-5 SCI connector (CN6) pin assignment.....	31
Table 6-6 LED pin assignment	31
Table 6-7 SPI communication pin assignment (CN8)	32
Table 6-8 Pmod Type 3A connector pin assignment (CN11).....	32
Table 6-9 Pmod Type 6A connector through hole pin assignment (CN7).....	32
Table 7-1 SCI connector (CN5) pin assignment.....	33
Table 7-2SCI connector (CN4) pin assignment.....	33

1. Overview

MCK-RX14T is a motor control evaluation kit. By using this product, motor control with MCK-RX14T can be performed easily.

MCK-RX14T has characteristics shown below.

- (1) Supports Brushless DC motor.
- (2) Supports 1-/2-/3-shunt current detection.
- (3) Supports Motor Control Development Support Tool (Renesas Motor Workbench).
- (4) Provides overcurrent protection function using overcurrent detection circuit.

1.1 Presupposition and precautions of this document

- 1. Experience of using tools: This document assumes that the user has used terminal emulation program of Integrated Development Environment (IDE) such as e² studio before.
- 2. Knowledge about the development subject: This document assumes that the user has a basic knowledge to modify the sample project regarding MCU and embedded system.
- 3. Before using this product, wear an antistatic wrist strap. If you touch this product with static charge on your body, a device failure may occur, or operation may become unstable
- 4. All screen shots provided in this document is for reference. Actual screen displays may differ depending on the software and development tool version which you use.

2. Product Contents

This kit consists of the following parts.

1. Inverter Board (RTK0EM0000B12020BJ) x1
2. CPU Board (RTK0EMXH30C00000BJ) x1
3. Communication board (RTK0EMXC90Z00000BJ) x1
4. Brushless DC Motor (R42BLD30L3) x1
5. Communication cable x1
6. USB cable x1
7. Screw x12
8. Standoff x12




Figure 2-1 Product contents

3. Product Order Information

Product number to ordering this product	Included item
RTK0EMXH30S00020BJ (MCK-RX14T)	CPU Board (RTK0EMXH30C00000BJ) Inverter Board (RTK0EM0000B12020BJ) Brushless DC Motor (R42BLD30L3) Communication board (RTK0EMXC90Z00000BJ) Communication cable USB cable

Product number for ordering included item	Included item
RTK0EMXH30C00000BJ (MCB-RX14T)	CPU Board (RTK0EMXH30C00000BJ)
RTK0EM0000S04020BJ (MCI-LV-1)	Inverter Board (RTK0EM0000B12020BJ) Brushless DC Motor (R42BLD30L3)
RTK0EMXC90S00000BJ (MC-COM)	Communication board (RTK0EMXC90Z00000BJ) Communication cable USB cable

4. Hardware Configuration and Default Setting

4.1 Hardware configuration

MCK-RX14T consists of the inverter board, the CPU board and the communication board. Specifications as a kit and for the relevant boards are listed below.

Table 4-1 MCK-RX14T specification (1/4)

Item	Specification	
Kit product name	MCK-RX14T	
Kit product No.	RTK0EMXH30S00020BJ	
Kit configuration	Inverter Board	RTK0EM0000B12020BJ
	CPU Board	RTK0EMXH30C00000BJ
	Communication board	RTK0EMXC90Z00000BJ
	Brushless DC Motor	R42BLD30L3 (MOONS') Rated voltage : 36[V] Rated current : 1.13[A]
Isolation	Inverter board - CPU board : Non-isolated Communication board – CPU board : isolated (up to 1kV _{RMS})	
External view	 Note: The actual product may differ from this photo.	
Board size	Inverter board : 133 mm (W) x 109 mm (L) CPU board : 109 mm (W) x 109 mm (L) Communication board : 89mm(W) × 52mm(L)	
Operating temperature	Room temperature	
Operating humidity	No condensation allowed	
EMC Directive	EN61326-1 : 2021 EMI : Class A EMS : Industrial Electromagnetic environment	

Table 4-2 MCK-RX14T specification (2/4)

Item	Specification
Product name	Inverter board
Board part No.	RTK0EM0000B12020BJ
External view	 Note: The actual product may differ from this photo.
Power supply	2 ways • From DC jack or Power supply connector (DC 12~48V) *1 • From CPU board (DC 5V)
Rated output current	AC 10 A (RMS value) *2
Switching frequency	20 kHz (typical)
Current detection method	1- / 2- / 3-shunt detection
Shunt resistor	10 mohm
PWM logic	Low side, High side : Positive logic
DC bus voltage detection (bus voltage detection)	Detection by resistance division (0 V ~ 48 V)
3-phase output voltage detection	Detection by resistance division (0 V ~ 48 V)
3-phase output current detection	With shunt resistor
Overcurrent detection function	21.4 A for AVCC=3.3V 32.4 A for AVCC=5.0V
Supporting sensor	HALL sensor, Encoder
Connector	• CPU card connector • Motor connector • Power input connector • HALL sensor connector • Encoder/Inductive position sensor connector
Switch	• Toggle switch x1 • Push switch x1
LED	• LED x3 • Power LED

*1 The polarity of the DC jack (J1) is center positive. The compatible plug has an inner diameter of 2.1 mm and an outer diameter of 5.5 mm.

*2 It is strongly recommended to attach a heat sink to the MOSFET when using over 5A.

Table 4-3 MCK-RX14T specification (3/4)

item		Specification
Product name		CPU Board
Board part No.		RTK0EMXH30C00000BJ
Compatible inverter board		RTK0EM0000B12020BJ
External view		 Note: The actual product may differ from this photo.
Mounted MCU	Product group	RX14T group
	Product No.	R5F514T5AMFM
	CPU maximum operating frequency	48MHz
	Bit count	32 bit
	Package / Pin count	LFQFP / 64 pin
	ROM	128KB
MCU input clock		48MHz (Generate with on-chip oscillator)
Power supply		DC 5V,3.3V (selectable with jumper pin) Select one way automatically from the below • Power is supplied from compatible inverter board • Power is supplied from USB connector
Debugger		E2OB (Onboard debugger circuit)
Connector		• Inverter board connector • USB connector for E2OB • SCI connector for Renesas Motor Workbench communication • Through hole for SPI communication • Pmod connectors
Switch		MCU reset switch
LED		User-controllable LED x5, Power LED x1

Table 4-4 MCK-RX14T specification (4/4)

item		Specification
Product name		Communication Board
Board part No.		RTK0EMXC90Z00000BJ
External view		 Note: The actual product may differ from this photo.
Mounted MCU	Product group	RX72N group
	Product No.	R5F572NNDDFB
	CPU maximum operating frequency	240MHz
	Bit count	32 bit
	Package / Pin count	LFQFP / 144 pin
	RAM	1M byte
MCU input clock		20MHz (Generate with external crystal oscillator)
Power supply		DC 5V Power is supplied from USB connector
Connector		- USB Type-C connector for PC - SCI connector for CPU board - USB miniB connector (not available for users)
Isolation		- Between SCI connector and MCU - Up to 1kV_{RMS}
Switch		MCU external reset switch

4.2 Block diagram




Figure 4-1 MCK-RX14T block diagram

4.3 Board Layout




Figure 4-2 Inverter board Layout




Figure 4-3 CPU Board Layout




Figure 4-4 Communication board Layout

4.4 Standoffs and Screws

Before using this product, assemble the included standoffs and screws as shown below.




Figure 4-5 Standoffs and Screws assembly

4.5 Jumper pin setting

4.5.1 Inverter board

Default settings and functions of the jumper pins (JP1~JP15) are as follows.

Table 4-5 Jumper pin setting of Inverter board

JP No.	Default setting	Function
JP1	2-3pin short	1-2pin short : Disable 5V regulator 2-3pin short : Enable 5V regulator
JP2, JP3, JP4, JP6, JP12, JP13	2-3pin short	1-2pin short : Disable current detection amplifiers 2-3pin short : Enable current detection amplifiers
JP5, JP7, JP9, JP10, JP14, JP15	1-2pin short	1-2pin short : Current detection amplifier gain = 20 1-2pin open : Current detection amplifier gain = 10
JP8, JP11	1-2pin short	1-2pin short : 2-/3-shunt current detection 2-3pin short : 1-shunt current detection




Figure 4-6 Default jumper pin setting of Inverter board

4.5.2 CPU board

Default settings and functions of the jumper pins (JP1~JP10) are as follows.

Table 4-6 Jumper pin setting of CPU board

JP No.	Function	Setting (function in use)			Default setting
		open	1-2 short	2-3 short	
1	IU(INV2)/VU(INV1) select	N/A	IU(INV2)	VU(INV1)	1-2 short
2	IV(INV2)/VV(INV1) select	N/A	IV(INV2)	VV(INV1)	1-2 short
3	IW(INV2)/VW(INV1) select	N/A	IW(INV2)	VW(INV1)	1-2 short
4	VR(INV2)/HV temp select	N/A	VR(INV2)	HV temp	1-2 short
5	UN(INV2)/PFCPWM1 select	N/A	UN(INV2)	PFCPWM1	1-2 short
6	VN(INV2)/PFCPWM2 select	N/A	VN(INV2)	PFCPWM2	1-2 short
7	SMOSI6(INV1)/PFCPWM2 select	N/A	SMOSI6(INV1)	PFCPWM2	1-2 short
8	E2OB (Onboard debugger)	E2OB enable	E2OB disable	N/A	1-2 short
9	blocking diode	D2 enable	D2 disable	N/A	JP9 unmounted part
10	MCU voltage select	N/A	5V	3.3V	1-2 short

PFC : Power Factor Correction




Figure 4-7 Default jumper pin setting of CPU board

4.5.3 Communication board

Default settings and functions of the jumper pins (JP1~JP3) are as follows.

Table 4-7 Jumper pin setting of Communication board

Jumper pin	Default setting	Function
JP1	1-2pin open	1-2pin short : Enable pull-up for MD port (Not available) 1-2pin open : Enable pull-up for MD port
JP2	1-2pin short	1-2pin short : Disable pull-up for GPIO(PC6) 1-2pin open : Enable pull-up for GPIO(PC6)
JP3	1-2pin short	1-2pin short : Disable pull-up for GPIO(PC5) 1-2pin open : Enable pull-up for GPIO(PC5)




Figure 4-8 Default jumper pin setting of Communication board

4.6 Hardware Setup

4.6.1 Board Connection

When using this product for motor control evaluation, connect the boards as shown in Figure 4-9. Note that the connector between the CPU board and the inverter board is a tight fit, so be careful not to bend the pins when connecting or disconnecting.

Please refer to 4.6.2 for the power supply method. In Figure 4-9 the power is supplied from the AC adaptor. The RX14T CPU board supports a maximum of two-motor control and can be connected as shown in Figure 6-2 shown later, if you prepare an additional inverter board and motor.




Figure 4-9 Board connection

4.6.2 Power Supply

There are three ways to supply power to the CPU board and inverter board, and the power supply for the communication board is independent of the CPU board and inverter board and is supplied at 5V from the USB connector.

(1) From DC jack

Use an AC adapter or something similar to supply power from the DC jack (J1) on the inverter board. The compatible plug has an outer diameter of 5.5 mm, an inner diameter of 2.1 mm, and a polarity of center positive. The input voltage range is 12 to 48V.



Figure 4-10 Power supply from DC jack

(2) From terminal block

Supply power from the terminal block (CN1) of the inverter board using a DC stabilized power supply or the like. The polarity should follow the silk indication ("+", "-") on the board. The input voltage range is 12 to 48V.



Figure 4-11 Power supply from terminal block

(3) From USB connector

5V power is supplied from the USB Type-C connector on the CPU board. Use a USB adapter capable of outputting 1A or more so that the motor can be driven sufficiently.



Figure 4-12 Power supply from USB connector

It is also possible to supply power from the USB connector on the CPU board and the DC jack or terminal block on the inverter board at the same time. In this case, the MCU drive voltage of 3.3V and the gate driver drive voltage are generated from the USB supply of 5V, while the motor drive voltage is supplied from the DC jack or terminal block. Please refer to Table 4-8 for the power supply conditions and each voltage generation.

Table 4-8 Power supply and driving voltage generation

			Case 1	Case 2	Case 3
Power supply condition	CPU board	USB 5V *1	✓	-	✓
	Inverter board	External power (12~48V) *2	-	✓	✓
Power source for	CPU board	I/O (VCC, 3.3V)	[A]	[B]	[A]
		BUS (5V)	[A]	[B]	[A]
	Inverter board	I/O (VCC, 3.3V)	[A]	[B]	[A]
		BUS (5V)	[A]	[B]	[A]
		Gate driver (11.4V)	[A]	[B]	[A]
		Motor drive (11.4V or 12~48V)	[A]	[B]	[B]

Power supply condition:

✓ : supplied

- : not supplied

Driving voltage generation

[A]: generated from USB 5V on CPU board

[B]: generated from external power on inverter board

*1 Motor drive current of 1A or more may be required for each inverter board.

*2 When connecting two inverter boards to the CPU board and also inputting an external power supply to INV2, it is necessary to supply an external power supply (which can be different from INV2) to INV1 as well, or to supply USB 5V to the CPU board.

5. Inverter Board Specification

This section describes inverter board specification.

5.1 Functions

5.1.1 Inverter control circuit block

The inverter board has the inverter control circuit block which controls the motor with 6 POWER MOSFETs. POWER MOSFET is controlled with 6-phase timer output of MCU.

The inverter control circuit block outputs DC bus voltage, U, V and W phase voltage and shunt current to the connectors (CN3, CN4). By inputting these output voltages to A/D of MCU on the CPU card, analog values of the voltage and the shunt current of each phase can be measured. Refer to

5.1.2 for the current detection and refer to 5.1.4 for the voltage detection, respectively. Also function to detect overcurrent from the input current is available. Refer to 5.1.3 for details.

An illustration of the inverter control circuit block is shown in Figure 5-1. In the actual circuit, some inputs on the A/D pins are via voltage dividers and offsets and so on. Refer to the circuit diagram for details.




Figure 5-1 Illustration of inverter control circuit block

5.1.2 Current detection circuit

The inverter board has the current detection circuit to measure the current at the U, V and W phase. The current detection circuit uses shunt resistor at each phase. Voltage drop caused by the current flowing through the shunt resistor is amplified by the current detection amplifier to output. The default gain of the current detection amplifier is set to 20x, but the gain can be changed to 10x by setting JP5, JP7, JP9, JP10, JP14, and JP15 to open. The relationship between the current I_{in} flowing through the shunt resistor and the voltage V_{out} output from the current detection circuit is shown in equations (1) and (2). In addition, by switching JP8 and JP11 to 2-3 pin short circuit, 1-shunt current detection can be supported.

$$\text{Amplifier gain 10x : } V_{out}[V] = I_{in}[A] \times R_s[\Omega] \times 10 + AVCC/2 \quad (1)$$

$$\text{Amplifier gain 20x : } V_{out}[V] = I_{in}[A] \times R_s[\Omega] \times 20 + AVCC/2 \quad (2)$$




Figure 5-2 Current detection circuit

5.1.3 Overcurrent detection circuit

Detect the overcurrent from the input current, using the overcurrent detection circuit illustrated in Figure 5-3. If the current value is within the range of threshold, OC_INV_OUT is HIGH, and this changes to LOW if overcurrent is detected. Therefore, you can protect the board and motor by monitoring the over current detection signal and setting PWM signals for gate driver to LOW or Hi-Z if the over current detection signal changes to LOW. As the value of the shunt resistor R_s is 10 m Ω , the threshold current for over current detection is 21.4A for AVCC=3.3V and 32.4A for AVCC=5.0V, respectively.

The overcurrent detection circuit does not directly protect the board and motor. Protect them by performing appropriate processing with equipment such as microcontroller.




Figure 5-3 Overcurrent detection circuit

5.1.4 Output voltage detection circuit

The inverter board has the circuit that inputs bus voltage and three-phase output voltage (U, V and W phase) into the AD pin of the microcontroller through resistive voltage divider. Relation between the three-phase output voltage, the bus voltage and the detection voltage is described by the below equation (3).

$$V_{out}[V] = \frac{470}{10 \times 10^3 + 470} \times V_{in}[V] \quad (3)$$




Figure 5-4 Output voltage detection circuit

5.1.5 Voltage generation circuit

On the inverter board, the gate driver voltage ("12V" in the schematic) is generated from the 5V power supply ("5V" in the schematic) with the boost converter. If 5V is not supplied from the CPU board, the buck converter on the inverter board generates 5V from the voltage input (12 to 48V) from the DC jack or terminal block.

Table 5-1 Voltage generation

Item	Input voltage [V]	Output voltage (TYP.) [V]	Output current (Max) [A]
5V generation	12~48	5	0.6
Gate driver voltage generation	5	11.4	-

5.1.6 LED

The inverter board has three LEDs which the user can control. The LED ON/OFF is controlled by the pin state.

Table 5-2 LED

Connector pin		LED1	LED2	LED3
CN4-18	HIGH	OFF	-	-
	LOW	ON	-	-
CN4-19	HIGH	-	OFF	-
	LOW	-	ON	-
CN4-20	HIGH	-	-	OFF
	LOW	-	-	ON

5.1.7 Toggle switch and push switch

The inverter board has toggle switch (SW1) and push switch (SW2). The pin voltage is controlled by the state of them.

Table 5-3 Toggle switch and push switch

Connector pin		SW1	SW2
CN4-16	HIGH	ON	-
	LOW	OFF	-
CN4-17	HIGH	-	RELEASE
	LOW	-	PUSH

5.1.8 Variable resistor

The inverter board has a variable resistor (VR1). If turning the variable resistor clockwise, terminal voltage of the variable resistor (CN3-17) becomes low. If turning it counterclockwise, the voltage becomes high.

Table 5-4 Variable resistance specification

Item	Specification
Input voltage range	0~AVCC
Variable resistor range	0~10kΩ

5.2 Pin assignment

5.2.1 CPU board connector

Table 5-5 CPU board connector (CN3)

Pin No.	Output direction	Signal
1	-	SPARE1
2	-	AGND
3	To CPU	DC bus voltage detection
4	-	AGND
5	To CPU	U-phase current detection
6	To CPU	U-phase current detection (PGAVSS)
7	To CPU	V-phase current detection
8	To CPU	V-phase current detection (PGAVSS)
9	To CPU	W-phase current detection
10	To CPU	W-phase current detection (PGAVSS)
11	To CPU	U-phase voltage detection
12	To CPU	V-phase voltage detection
13	To CPU	W-phase voltage detection
14	-	AGND
15	To CPU	VPFC_AD
16	To CPU	IPFC_AD
17	To CPU	VR1
18	-	AGND
19	-	AVCC
20	-	AVCC
21	-	AGND
22	-	AGND
23	-	VCC
24	-	VCC
25	-	DGND
26	-	DGND
27	To INV	PWM UL
28	-	DGND
29	To INV	PWM UH
30	-	DGND
31	To INV	PWM VL
32	-	DGND
33	To INV	PWM VH
34	-	DGND

Table 5-6 CPU board connector (CN4)

Pin No.	Output direction	Signal
1	To INV	PWM WL
2	-	DGND
3	To INV	PWM WH
4	-	DGND
5	-	SPARE2
6	-	SPARE3
7	-	SPARE4
8	-	SPARE5
9	To INV	Bus power signal from CPU board
10	To CPU	Inverter connected signal
11	To CPU	Save interlock signal
12	To CPU	Over current detection
13	To CPU	OC_PFC_OUT
14	To INV	PWM_IN
15	To INV	RELAY_IN
16	To CPU	SW1
17	To CPU	SW2
18	To INV	LED1
19	To INV	LED2
20	To INV	LED3
21	To CPU	HALL U
22	To CPU	HALL V
23	To CPU	HALL W
24	To CPU	IPS_SIO_SDA
25	To CPU	IPS_SCK_SCL
26	To CPU	IPS_CSN_IRQN/Encoder Z
27	To CPU	IPS_A/ Encoder A
28	To CPU	IPS_A#/ Encoder A#
29	To CPU	IPS_B/ Encoder B#
30	To CPU	IPS_B#/ Encoder B#
31	-	GND
32	-	GND
33	-	+5V
34	-	+5V

5.2.2 Hall sensor signal input

This product has connector for hall sensor signal input. Pin assignment of it is listed in Table 5-7.

Table 5-7 Connector for hall sensor signal input (CN6) pin assignment

Pin No.	Pin Function
1	DGND
2	+5V
3	HALL_W
4	HALL_V
5	HALL_U

5.2.3 Encoder/Inductive position sensor signal input

This product has connector for encoder/inductive position sensor signal input. Pin assignment for them is listed in Table 5-8.

Table 5-8 Connector for encoder/inductive position sensor signal input (CN5) pin assignment

Pin No.	Pin function
1	VCC
2	+5V
3	CSN_IRQN/ENC_Z
4	SIO_SDA
5	SCK_SCL
6	IPS_A/ENC_A
7	IPS_A#/ENC_A#
8	IPS_B/ENC_B
9	IPS_B#/ENC_B#
10	DGND

6. CPU Board Specification

This section describes the specification of the CPU Board.

6.1 Functions

6.1.1 Power supply

When not connected to the inverter board, power should be supplied from the USB connector(CN9). When connecting to the inverter board, power supply from the USB connector or from the inverter board will be automatically selected. USB power supply has priority. The MCU operation voltage can be selected at either 5 V or 3.3 V for this product. The operation voltage is switched with JP10 as shown in Table 4-6.

6.1.2 On-board debugger

This product has the on-board debugger circuit, E2 On-Board (hereinafter called "E2OB"). You can write a program (firmware) of RX14T with it. When you write a program, open (remove) JP8 and connect the CPU board to PC with USB cable. E2OB operates as debugger equivalent to E2 emulator Lite. If connecting from Integrated Development Environment (e.g. e² studio) or flash programming tool (e.g. Renesas Flash Programmer), set the type of debugger (tool) to "E2 emulator Lite".

After writing a program, short JP8 for CPU board operation.

JP8

open : enable on-board debugger

short : disable on-board debugger



Figure 6-1 JP8 setting

6.1.3 Inverter board connector

Max 2 inverter boards can be connected to this product. 1st inverter board is connected with CN1 and CN2, and 2nd inverter board is connected with CN3 and CN4. The pin assignments of the connectors are shown in Table 6-1, Table 6-2, Table 6-3, Table 6-4.

Table 6-1 1st inverter board connector (CN1) pin assignment

Pin No.	Pin Function	RX14T Pin	Pin No.	Pin Function	RX14T Pin
1	HVtemp	P46/AN006(*)	2	AGND	- (VSS/AVSS0)
3	VBUS	P11/AN102	4	AGND	- (VSS/AVSS0)
5	IU	P41/AN001	6	NC	-
7	IV	P42/AN002	8	NC	-
9	IW	P40/AN000	10	NC	-
11	VU	P15/AN107(*)	12	VV	P44/AN004(*)
13	VW	P45/AN005(*)	14	AGND	- (VSS/AVSS0)
15	VAC	P12/AN104	16	IPFC	P43/AN003
17	VR	P10/AN103	18	AGND	- (VSS/AVSS0)
19	AVCC	- (VCC/AVCC0)	20	AVCC	- (VCC/AVCC0)
21	AGND	- (VSS/AVSS0)	22	AGND	- (VSS/AVSS0)
23	VCC	- (VCC/AVCC0)	24	VCC	- (VCC/AVCC0)
25	GND	- (VSS/AVSS0)	26	GND	- (VSS/AVSS0)
27	UN	P76/MTIOC4D	28	GND	- (VSS/AVSS0)
29	UP	P73/MTIOC4B	30	GND	- (VSS/AVSS0)
31	VN	P75/MTIOC4C	32	GND	- (VSS/AVSS0)
33	VP	P72/MTIOC4A	34	GND	- (VSS/AVSS0)

(*) Exclusively assigned by jumper pin and jumper register setting

Table 6-2 1st inverter board connector (CN2) pin assignment

Pin No.	Pin Function	RX14T Pin	Pin No.	Pin Function	RX14T Pin
1	WN	P74/MTIOC3D	2	GND	- (VSS/AVSS0)
3	WP	P71/MTIOC3B	4	GND	- (VSS/AVSS0)
5	DRV_SCK	PB2/SCK6	6	PFCPWM2/ DRV_RXD	PB0/GTIOC1B(*) PB3/SMOSI6(*)
7	DRV_TXD	PB4/SMISO6	8	DRV_CS	PB7/SS6#
9	BUS_POWER_IN	-	10	INV_CONNECTED	-
11	SAFE_LOCK	-	12	OCINV	P30/POE11#
13	OCFPC/DRV_nFault	P36/IRQ3	14	PFCPWM1/DRV_EN	PB1/GTIOC2B(*)
15	Relay/CON_MOT_SEL	P91	16	SW1	PD7
17	SW2	PE2	18	LED1	PD3
19	LED2	PD4	20	LED3	PD6
21	HALL_U	P92/IRQ0	22	HALL_V	P93/IRQ1
23	HALL_W	P90/IRQ6	24	NC	-
25	NC	-	26	ENC_Z	P70/IRQ5
27	ENC_A	P33/MTCLKA	28	NC	-
29	ENC_B	P32/MTCLKB	30	NC	-
31	GND	- (VSS/AVSS0)	32	GND	- (VSS/AVSS0)
33	+5V	-	34	+5V	-

(*) Exclusively assigned by jumper pin and jumper register setting

Table 6-3 2nd inverter board connector (CN3) pin assignment

Pin No.	Pin Function	RX14T Pin	Pin No.	Pin Function	RX14T Pin
1	NC	-	2	AGND	- (VSS/AVSS0)
3	VBUS	P47/AN007	4	AGND	- (VSS/AVSS0)
5	IU	P15/AN107	6	NC	-
7	IV	P44/AN004	8	NC	-
9	IW	P45/AN005	10	NC	-
11	NC	-	12	NC	-
13	NC	-	14	AGND	- (VSS/AVSS0)
15	NC	-	16	NC	-
17	VR	P46/AN006(*)	18	AGND	- (VSS/AVSS0)
19	AVCC	- (VCC/AVCC0)	20	AVCC	- (VCC/AVCC0)
21	AGND	- (VSS/AVSS0)	22	AGND	- (VSS/AVSS0)
23	VCC	- (VCC/AVCC0)	24	VCC	- (VCC/AVCC0)
25	GND	- (VSS/AVSS0)	26	GND	- (VSS/AVSS0)
27	UN	PB1/GTIOC2B(*)	28	GND	- (VSS/AVSS0)
29	UP	P96/GTIOC2A	30	GND	- (VSS/AVSS0)
31	VN	PB0/GTIOC1B(*)	32	GND	- (VSS/AVSS0)
33	VP	P95/GTIOC1A	34	GND	- (VSS/AVSS0)

(*) Exclusively assigned by jumper pin and jumper register setting

Table 6-4 2nd inverter board connector (CN4) pin assignment

Pin No.	Pin Function	RX14T Pin	Pin No.	Pin Function	RX14T Pin
1	WN	P97/GTIOC0B	2	GND	- (VSS/AVSS0)
3	WP	P94/GTIOC0A	4	GND	- (VSS/AVSS0)
5	NC	-	6	Pull Down	- (VSS/AVSS0)
7	NC	-	8	NC	-
9	BUS_POWER_IN	-	10	INV_CONNECTED	-
11	SAFE_LOCK	-	12	OCINV	P25/GTETRGA
13	NC	-	14	Pull Down	- (VSS/AVSS0)
15	Pull Down	- (VSS/AVSS0)	16	SW1	PB2
17	SW2	PB7/SS6#	18	LED1	P00
19	LED2	P01	20	NC	-
21	NC	-	22	NC	-
23	NC	-	24	NC	-
25	NC	-	26	NC	-
27	NC	-	28	NC	-
29	NC	-	30	NC	-
31	GND	- (VSS/AVSS0)	32	GND	- (VSS/AVSS0)
33	+5V	-	34	+5V	-

Figure 6-2 show a connection example when using this product with the inverter board and the communication board. And also see 4.6.2 for power supply.




Figure 6-2 Board connection of CPU board, INV board and COM board

6.1.4 Serial communication

For serial communication using Renesas Motor Workbench, the CPU board has SCI connector. Pin assignment for SCI connector is listed in Table 6-5.

Table 6-5 SCI connector (CN6) pin assignment

Pin No.	Pin Function	RX14T Connection Pin
1	GND	- (VSS/AVSS0)
2	MCU RXD	P24/RXD5
3	MCU TXD	P23/TXD5
4	VCC	- (VCC/AVCC0)

6.1.5 Reset circuit

This product has a reset circuit to enable power-on reset or external reset on MCU. Push the reset switch (S1) to externally reset MCU.

6.1.6 LED

This product has 5 controllable LEDs, so that they can be used for program debug and the system. LED switches on when output from the corresponding port is "LOW" and switches off when output is "HIGH". Pin assignment for corresponding LEDs is listed in Table 6-6.

Table 6-6 LED pin assignment

RX14T pin output		LED1	LED2	LED3	LED4	LED5
PD3	HIGH	OFF	-	-	-	-
	LOW	ON	-	-	-	-
PD4	HIGH	-	OFF	-	-	-
	LOW	-	ON	-	-	-
PD6	HIGH	-	-	OFF	-	-
	LOW	-	-	ON	-	-
P00	HIGH	-	-	-	OFF	-
	LOW	-	-	-	ON	-
P01	HIGH	-	-	-	-	OFF
	LOW	-	-	-	-	ON

6.1.7 SPI Communication

This product has through holes for SPI communication. Pin assignment for SPI communication connector is listed in Table 6-7.

Table 6-7 SPI communication pin assignment (CN8)

Pin No.	RX14T pin
1	PB7/SS6#
2	PB3/SMOSI6
3	PB4/SMISO6
4	PB2/SCK6
5	- (VSS/AVSS0)
6	- (VCC/AVCC0)

6.1.8 Pmod

This product has one connector and one connector through hole for Pmod module connection. Pin assignments are shown in Table 6-8 and Table 6-9 .

Table 6-8 Pmod Type 3A connector pin assignment (CN11)

No.	RX14T port	No.	RX14T port
1	P02	7	P22/IRQ2
2	PB5/TXD1	8	P03
3	PB6/RXD1	9	P04
4	PD6/LED3	10	PD5
5	- (VSS/AVSS0)	11	- (VSS/AVSS0)
6	- (VCC/AVCC0)	12	- (VCC/AVCC0)

Table 6-9 Pmod Type 6A connector through hole pin assignment (CN7)

No.	RX14T port	No.	RX14T port
1	P22/IRQ2	7	P02
2	PB4/SMISO6	8	P03
3	P26/SCL0	9	P04
4	P31/SDA0	10	PD5
5	- (VSS/AVSS0)	11	- (VSS/AVSS0)
6	- (VCC/AVCC0)	12	- (VCC/AVCC0)

7. Communication Board Specification

This section describes the specification of the communication board.

7.1 Functions

7.1.1 Power supply

Power of this product is supplied at 5V from USB connector.

7.1.2 USB communication

This product is equipped with a USB Type-C connector for communication with a PC when using Renesas Motor Workbench, etc.

7.1.3 Serial communication

This board has two SCI connectors for serial communication with the target MCU when using Renesas Motor Workbench, etc. The pin assignments are shown in Table 7-1 and Table 7-2. When using the communication cable bundled with this product, use CN5.

The serial communication connector and the MCU (RX72N) are connected via a digital isolator, so the communication board and the CPU board with the target MCU are isolated.

Table 7-1 SCI connector (CN5) pin assignment

Pin No.	Function	Note
1	VCC	
2	RXD	Connect to TXD of target MCU
3	TXD	Connect to RXD of target MCU
4	GND	

Table 7-2SCI connector (CN4) pin assignment

Pin No.	Function	Note
1	VCC	
2	RXD	Connect to TXD of target MCU
3	TXD	Connect to RXD of target MCU
4	GND	

8. Regulatory information

This product meets the following standards. See page 2 of this user's manual for the precautions.

8.1 EMC Directive



This product is herewith confirmed to comply with the requirements set out in the Council Directives on the Approximation of the laws of the Member States relating to Electromagnetic Compatibility Directive 2014/30/EU.



This product is in conformity with the following relevant UK Statutory Instrument(s) (and its amendments): 2016 No. 1091 Electromagnetic Compatibility Regulations 2016.

Warning – This is a Class A product. In a domestic environment this product may cause radio interference in which case the user may be required to take adequate measures to correct this interference.

8.2 Material Selection, Waste, Recycling and Disposal Standards

- China SJ/T 113642014, 10-year environmental protection use period.
- WEEE Directive (2012/19/EU) & The Waste Electrical and Electronic Equipment Regulations 2013



The WEEE (Waste Electrical and Electronic Equipment) regulations put responsibilities on producers for the collection and recycling or disposal of electrical and electronic waste. Return of WEEE under these regulations is applicable in the UK and European Union.

This product (including all accessories) is not intended for household use. After use the product cannot be disposed of as household waste, and the WEEE must be treated, recycled and disposed of in an environmentally sound manner.

Renesas Electronics Europe GmbH can take back end of life product. Register for this service at; <https://www.renesas.com/form/weee-questionnaire>

9. Design and Manufacture Information

You can obtain information on the design and manufacture of this product from [renesas.com](https://www.renesas.com).

10. Website and Support

In order to learn, download tools and documents, apply technical support for RX family MCU and its kit, visit the below Web site.

- RX Product Information [renesas.com/rx](https://www.renesas.com/rx)
- Renesas Support [renesas.com/support](https://www.renesas.com/support)

Revision History

Rev.	Date	Description	
		Page	Summary
1.00	Sep 12, 2025	-	First edition

MCK-RX14T User's Manual

Publication Date: Rev 1.00 Sep 12, 2025

Published by: Renesas Electronics Corporation

MCK-RX14T User's Manual