



Calogic, LLC  
 237 Whitney Place  
 Fremont, CA 94539  
 Tel: 510-656-2900  
 Fax: 510-651-1076

JFET Amplifier Applications (Dual Amplifiers, N-Channel)						
P/ N	Idss (mA(min))	Igss (pA(max))	gfs (mS(min))	eN (nV/ rootHz) (typ)	Match (Vgs1- 2mV) (max)	Package
2N5911	7	-100	5.0	15	10	TO-78
2N5912	7	-100	5.0	15	15	TO-78
SST5911	7	-100	5.0	10	10	SO-8
SST5912	7	-100	5.0	10	15	SO-8
SST440	6	-500	4.5	10	10	SO-8
SST441	6	-500	4.5	10	20	SO-8
SST404	.5	-25	2.0	10	15	SO-8
SST405	.5	-25	2.0	10	20	SO-8
SST406	.5	-25	2.0	10	40	SO-8
U401	.5	-25	2.0	10	5	TO-71
U402	.5	-25	2.0	10	10	TO-71
U403	.5	-25	2.0	10	10	TO-71
U404	.5	-25	2.0	10	15	TO-71
U405	.5	-25	2.0	10	20	TO-71
U406	.5	-25	2.0	10	40	TO-71
U421	.06	-1.0	.3	50	10	TO-78
U422	.06	-1.0	.3	50	15	TO-78
U423	.06	-1.0	.3	50	25	TO-78
U424	.06	-3.0	.3	50	10	TO-78
U425	.06	-3.0	.3	50	15	TO-78
U426	.06	-3.0	.3	50	25	TO-78
U440	6.0	-500	4.5	10	10	TO-71
U441	6.0	-500	4.5	10	20	TO-71
U443	6.0	-500	4.5	10	10	TO-78
U444	6.0	-500	4.5	10	20	TO-78