



JQ CONNECTOR

Board-to-board connectors





This 2.5mm (.098") pitch connector is used to interconnect printed circuit boards. It easily resists distortion during mating, thus ensuring reliable contact, even under adverse conditions.



Features -

• High contact pressure

This vibration-resistant, double-beam contact provides high contact pressure and thus eliminates contact bounce during vibration or shock.

Box-shaped shroud

The four-sided shrouded header prevents the socket housing from being misinserted or distorted during mating. The slots in the header's shroud fit snugly into the receptacle housing, guaranteeing a vibration-proof coupling. And the serrated square posts are pressure-fit to prevent flux from entering during soldering.

· Secure locking on printed circuit boards

The solder tails of both the plug and receptacle have board retention features. This ensures secure mounting and accurate location during soldering.

Vertical, horizontal and parallel mounting

Both top-entry and side-entry receptacles and shrouded headers are available, thus allowing printed circuit boards to be connected vertically, horizontally or parallel to the mother board.

Interchangeability

The shrouded header is interchangeable with the XH wire-to-board crimp style connectors, the NR and NRD wire-to-board insulation displacement connectors.

Specifications -

Current rating: 3A AC, DC
Voltage rating: 250V AC, DC
Temperature range: -25°C to +85°C

(including temperature rise in applying

electrical current)

• Contact resistance: Initial value/10m Ω max.

After environmental testing/20m Ω max.

• Insulation resistance: 1,000M Ω min. • Withstanding voltage: 1,000V AC/minute • Applicable PC board thickness: 1.6mm(.063")

* Contact JST if Lead-Free product is required.

* Refer to "General Instruction and Notice when using Terminals and Connectors" at the end of this catalog.

* Contact JST for details.

Standards -


Recognized E60389

⑥ Certified LR20812

△ R75085

JQ CONNECTOR

Receptacle-



	Model No.		Dimensions mm(in.)			Q'ty / box	
Cir- cuits	Top entry type	Side entry type	А	В	С	Top entry type	Side entry type
3	03JQ-BT	03JQ-ST	5.0(.197)	10.0(.394)	8.2(.323)	500	500
4	04JQ-BT	04JQ-ST	7.5(.295)	12.5(.492)	10.7(.421)	500	500
5	05JQ-BT	05JQ-ST	10.0(.394)	15.0(.591)	13.2(.520)	500	500
6	06JQ-BT	06JQ-ST	12.5(.492)	17.5(.689)	15.7(.618)	500	500
7	07JQ-BT	07JQ-ST	15.0(.591)	20.0(.787)	18.2(.717)	250	250
8	08JQ-BT	08JQ-ST	17.5(.689)	22.5(.886)	20.7(.815)	200	250
9	09JQ-BT	09JQ-ST	20.0(.787)	25.0(.984)	23.2(.913)	200	250
10	10JQ-BT	10JQ-ST	22.5(.886)	27.5(1.083)	25.7(1.012)	250	250
11	11JQ-BT	11JQ-ST	25.0(.984)	30.0(1.181)	28.2(1.110)	250	250
12	12JQ-BT	12JQ-ST	27.5(1.083)	32.5(1.280)	30.7(1.209)	200	200
13	13JQ-BT	13JQ-ST	30.0(1.181)	35.0(1.378)	33.2(1.307)	200	200
15	15JQ-BT	15JQ-ST	35.0(1.378)	40.0(1.575)	38.2(1.504)	100	100

Material and Finish

Contact: Phosphor bronze, tin-plated Housing: Nylon 66, UL94V-0, natural


Note: 13JQ-BT, 13JQ-ST, 15JQ-BT & 15JQ-ST are not TÜV approved.

Shrouded header

The through-hole type shrouded headers are interchangeable with the XH crimp style connectors, the NR and NRD insulation displacement connectors.

JQ CONNECTOR

PC board layout (viewed from soldering side)-



Note:

- 1. Tolerances are non-cumulative: ± 0.05 mm($\pm .002$ ") for all centers.
- 2. Hole dimensions differ according to the kind of PC board and piercing method. The dimensions above should serve as a guideline. Contact JST for details.

Assembly layout -

Top entry type		Receptacle				
		Top entry type	Side entry type			
Shrouded	Top entry type B()B-XH-A	3.4(.134) 5.75(.226)	3.6(.142) (8)(5)(2)(2)(2)(2)(2)(2)(2)(2)(2)(2)(2)(2)(2)			
header	Side entry type S()B-XH-A-1	2.9(.114) 6.15(.242)	16.3 (.642) 2.6 (.102)min. 10.2(.402) 2.2(.087)			